



## Augmented nonlinear differentiator design



Xingling Shao<sup>\*</sup>, Jun Liu, Wei Yang, Jun Tang, Jie Li

Key Laboratory of Instrumentation Science & Dynamic Measurement, Ministry of Education, North University of China, Taiyuan 030051, China  
National Key Laboratory for Electronic Measurement Technology, School of Instrument and Electronics, North University of China, Taiyuan 030051, China

### ARTICLE INFO

#### Article history:

Received 24 September 2016

Received in revised form 22 November 2016

Accepted 20 December 2016

#### Keywords:

Augmented nonlinear differentiator (AND)

Noisy measurement

Noise-tolerance capability

Describing function

Autopilot design

Displacement following

### ABSTRACT

This paper presents a sigmoid function based augmented nonlinear differentiator (AND) for calculating the noise-less time derivative from a noisy measurement. The prominent advantages of the present differentiation technique are: (i) compared to the existing tracking differentiators, better noise suppression ability can be achieved without appreciable delay; (ii) the enhanced noise-filtering mechanism not only can be applied to the designed differentiator, but also can be extended for improving noise-tolerance capability of the available differentiators. In addition, the convergence property and robustness performance against noises are investigated via singular perturbation theory and describing function method, respectively. Also, comparison with several classical differentiators is given to illustrate the superiority of AND in noise suppression. Finally, applications on autopilot design and displacement following for nonlinear mass spring mechanical system are given to demonstrate the effectiveness and applicability of the proposed AND technique.

© 2016 Elsevier Ltd. All rights reserved.

## 1. Introduction

Measured signals obtained by physical sensors are inevitably corrupted by additive noises, such as electronic shocks, hardware noises or environment noises, among others. Differentiation of a noisy signal has attracted increasing attention from research community and the industry practitioners due to their widespread applications in a variety of engineering areas. The main design specification of differentiators is to calculate signal differentiation with adequate noise immunity level for the purposes of efficient control synthesis and implementation [1,2]. For example, an asymptotic differentiation approach of signal is incorporated with traditional feedback controller for estimating angular acceleration and achieving velocity regulation of DC motor, which greatly reduces the controller implementation cost [3]. In an analogous manner, a discrete-time variable-structure-based control strategy for permanent-magnet synchronous motor (PMSM) is developed by integrating with a speed reconstruction approach [4], where the first-order derivative of the encoder position measurement is obtained by a robust digital differentiator. In the field of navigation and control for aircrafts, carrier phase rate is determined through a nonlinear tracking differentiator (NTD) using carrier phase measurements from the Global Navigation Satellite System (GNSS) [5]. In [6], flight velocity and acceleration are successfully achieved from the position measurement by exploiting a high-order continuous nonlinear differentiator. Further extension of high-order differentiator with application to under-actuated quadrotor can be found in [7], wherein the estimation of velocity and uncertainties can be

<sup>\*</sup> Corresponding author at: Key Laboratory of Instrumentation Science & Dynamic Measurement, Ministry of Education, North University of China, Taiyuan 030051, China.

E-mail address: [shaoxl@nuc.edu.cn](mailto:shaoxl@nuc.edu.cn) (X. Shao).

synchronously extracted using the position measurement alone. In addition to the aforementioned scenarios that differentiators are applied in feedback channel, actively eliminating control saturation and 'derivative explosion' issue existed in the traditional back-stepping control framework can both be effectively dealt with by adopting NTD in feedforward channel [8–11]. Generally speaking, if the measurement noise is sufficiently large, the corrupted differential signals used in the feedback or feedforward loops may severely destabilize the closed-loop system, thus robustness performance against noise perturbation, the convergent rate and ease of implementation are all significant factors in the assessment of differential estimation quality.

To achieve a satisfactory differential estimation with good convergence property, many researchers have dedicated to developing various differentiators. A sliding mode technique based differentiator is proposed under the assumption that knowledges on the upper bound of the derivative of input signal is available [12]. Nevertheless, this assumption can seldom be satisfied in practice. A finite-time-convergent differentiator is developed in [13], but chattering phenomenon in differential estimation is inevitable, such disadvantage constrains its use in practical engineering. In [14], NTD using a second-order optimal acceleration function with one switching term is proposed. However, it suffers from the drawback of limited convergent speed. To improve the rapidity, since the dynamic response of TD is mainly dependent on the appropriate selection of acceleration function, pioneering contributions on constructing more efficient differentiators with various acceleration functions are extensively investigated, including power function [15], finite-time-convergent function [13] and sigmoid function [16,17]. Among which, sigmoid tracking differentiator (STD) naturally integrates the benefits of the characteristics of the existing linear and nonlinear differentiators, and possesses the property of globally fast convergent speed, the property of which will be further exploited in the paper. Furthermore, the phase lag of differentiator is addressed by the employment of feedforward action [18], in which the magnitude characteristics of resultant differentiator is close to that of the ideal differentiator, implying that the improvement in convergent speed benefiting from feedforward is achieved at the expense of sacrificing noise filtering property. Thus, it is definitely not suitable for handling the measurement noise in signal differentiation.

It should be pointed out that the existing design framework of differentiators are formulated in high-gain techniques, indicating that they may dangerously amplify the measurement noise in its differential estimates when a high gain is used, irrespective of how acceleration function is selected. In addition, since the tradeoff always exists between the speed of state recovery and the immunity to measurement noise in observer theory [19], the existing differentiators have to compromise between the noise filtering and state reconstruction speed, i.e., better noise-filtering property in signal differentiation is often achieved at the expense of noticeable time delay. Furthermore, no specific manipulation on noise elimination is taken into account in differentiator design. Therefore, the available differentiators have limited robustness against measurement noise and fall short of supplying a differential estimate with adequate noise immunity level. And how to further relax the contradictory and enhance the noise attenuation ability becomes an imperative and challenging problem, which should be addressed by exploring advanced signal differentiation approaches that will not only provide a rapid estimate, but will also guarantee smooth and noise-less property.

Motivated by the above analysis, to overcome the limitation of the existing differentiators in handling measurement noise and take advantages of STD in fast convergent rate, a sigmoid function based augmented nonlinear differentiator (AND) is proposed for calculating the noise-less time derivative from a noisy measurement. It is worth noting that the improved mechanism not only can be confined to the designed differentiator, but also can be suitable for enhancing noise-filtering capability of the existing differentiators, which further enriches the theoretical content of differentiators. The main contributions in this paper are summarized as follows.

- The idea of augmenting the signal dynamics with integrated noisy output to account for eliminating noises is firstly proposed under differentiator framework, based on which, an augmented nonlinear differentiator (AND) based on sigmoid function is developed, which can be treated as an extension of STD from theoretical structure perspective, since the noise filtering ability in differential estimate is enhanced while good convergence property is also retained. In addition, the proposed noise-tolerance technique can be easily extended to transform the available tracking differentiators to augmented differentiators with improved signal-to-noise ratio, irrespective of how acceleration function is selected.
- The convergence property and robustness performance against noise are investigated via singular perturbation theory and describing function method, respectively. Also, the effect of parameters of observer on the dynamic performance of AND is provided as the guideline for tuning parameter gains in differentiators.
- Application on autopilot design and displacement following for nonlinear mass spring mechanical system in the presence of measurement noise are illustrated to validate the effectiveness of the proposed AND, where a linear attitude controller is implemented to track the given attitude command using the noisy pitch angle only and a output feedback based displacement following controller is developed for mass spring mechanical system under disturbance observer-based control (DOBC) framework.

The paper is organized as follows. Some Preliminaries and Problem formulation are introduced in Section 2. In Section 3, main results on the proposed AND are given. In Section 4, frequency analysis is presented. Comparison and Application is shown in Section 5. The paper ends with a few concluding remarks in Section 6.

Download English Version:

<https://daneshyari.com/en/article/4977050>

Download Persian Version:

<https://daneshyari.com/article/4977050>

[Daneshyari.com](https://daneshyari.com)