Contents lists available at ScienceDirect

### Signal Processing

journal homepage: www.elsevier.com/locate/sigpro

#### Short communication

# On the reconstruction of nonsparse time-frequency signals with sparsity constraint from a reduced set of samples<sup> $\star$ </sup>



<sup>a</sup> Faculty of Electrical Engineering, University of Montenegro, Podgorica 81000, Montenegro <sup>b</sup> GIPSA Lab, INP Grenoble, University of Grenoble Alpes, Saint-Martin-d'Hères 38400, France

#### ARTICLE INFO

Article history: Received 1 February 2017 Revised 2 June 2017 Accepted 30 July 2017 Available online 4 August 2017

Keywords: Time-frequency analysis Sparsity Reconstruction Compressive sensing

#### 1. Introduction

Nonstationary signals that cover most of the time and frequency domain may be well localized in the joint time-frequency domain. These signals are dense in both time and frequency, considered separately. However, they could be located within much smaller regions in the joint domain using appropriate representations [1–6]. The basic time-frequency representation is the shorttime Fourier transform (STFT). It can be easily related to the Wigner distribution and its cross-terms reduced versions [7]. These representations will be considered in this paper. The signals are sparse in the time-frequency domain if the number of nonzero coefficients in this domain is much smaller than the total number of coefficients. For example, a sum of few nonstationary signal components, being well localized in the STFT at each considered time instant, is a sparse signal in this domain.

A signal that is sparse in a certain domain can be reconstructed with fewer samples than the Shannon–Nyquist sampling theorem requires. Compressive sensing is the field dealing with the problem of signal recovery with reduced number of available samples [8–14]. Reducing the number of available samples in the analy-

\* Corresponding author at: Faculty of Electrical Engineering, University of Montenegro, Podgorica 81000, Montenegro.

#### ABSTRACT

Nonstationary signals, approximately sparse in the joint time-frequency domain, are considered. Reconstruction of such signals with sparsity constraint is analyzed in this paper. The short-time Fourier transform (STFT) and time-frequency representations that can be calculated using the STFT are considered. The formula for error caused by the nonreconstructed coefficients is derived and presented in the form of a theorem. The results are examined statistically on examples.

© 2017 Elsevier B.V. All rights reserved.

sis manifests as a noise, whose properties in the discrete Fourier transform (DFT) domain are studied in [15]. These results will be used to define reconstruction properties in the STFT case. The influence of noise in the two-dimensional DFT is examined in [16]. If a nonsparse signal is reconstructed with a reduced set of available samples then the noise due to the missing samples of nonreconstructed coefficients will be considered as an additive input noise in the reconstructed signal.

In the compressive sensing literature, only the general bounds for the reconstruction error for nonsparse signals (reconstructed with the sparsity assumption) are derived [10,17,18]. In this manuscript, we have presented an exact relation for the expected squared error in approximately sparse or nonsparse signals in the time-frequency domain, reconstructed from a reduced set of signal samples, under the sparsity constraint. The error depends on the number of available samples and the assumed sparsity, that is crucial for any compressive sensing based reconstruction. The results are given in the form of a theorem. Theory is illustrated and checked on statistical examples.

The noise in the reconstructed STFT influences other timefrequency representations that can be calculated using this STFT. The S-method [6,7] is considered as an example of such signal representations.

The paper is organized as follows. The theoretical background of compressive sensing and time-frequency signal analysis is presented in Section 2. The theorem and formula of nonsparsity influence on the reconstructed signal is presented in Section 3. The numerical results are given in Section 4. The conclusions are presented in Section 5.





 $<sup>^{\</sup>star}$  This work is supported by the Montenegrin Ministry of Science, project grant funded by the World Bank (Grant no. 01-1002) loan: CS-ICT "New ICT Compressive sensing based trends applied to: multimedia, biomedicine and communications"

*E-mail addresses*: isidoras@ac.me (I. Stanković), cornel.ioana@gipsa-lab.grenobleinp.fr (C. Ioana), milos@ac.me (M. Daković).

#### 2. Theoretical background

Let us consider a multicomponent signal

$$x(n) = \sum_{l=1}^{C} x_{l}(n),$$
(1)

where components  $x_l(n)$  are nonstationary and the total number of components is C. Assume that the signal is sparse in the STFT domain. The STFT of the discrete-time signal is defined as

$$S_N(n,k) = \sum_{m=-N/2}^{N/2-1} x(n+m)w(m)e^{-j\frac{2\pi}{N}mk},$$
(2)

at an instant *n* and a frequency *k*. The window function of length *N* is w(m). The windowed signal x(n, m) = x(n+m)w(m), which is *K*-sparse in the STFT domain, can be written in the form

$$x(n,m) = \sum_{i=1}^{K} A_i(n) e^{j2\pi m k_i/N}.$$
(3)

The signal and its STFT in a vector form are

$$\mathbf{S}_{N}(n) = \mathbf{W}_{N}\mathbf{H}_{N}\mathbf{x}(n) \tag{4}$$

$$\mathbf{H}_{N}\mathbf{x}(n) = \mathbf{W}_{N}^{-1}\mathbf{S}_{N}(n), \tag{5}$$

where  $\mathbf{S}_N(n) = [S_N(n, 0), S_N(n, 1), \dots, S_N(n, N-1)]^T$  is the STFT calculated at time instant n,  $\mathbf{x}(n)$  is the original signal (column) vector within the window,  $\mathbf{W}_N$  is the DFT matrix of size  $N \times N$  with coefficients  $W(m, k) = e^{(-j2\pi km/N)}$  and  $\mathbf{H}_N$  is a diagonal matrix with the window values at its diagonal. Analysis and reconstruction of the whole signal based on the STFT is straightforward with appropriate overlapping. It is presented in [1,2,6].

With the assumption that the signal is sparse in the STFT domain, we can reconstruct it with a reduced number of samples, according to the compressive sensing theory [8,10,17,18,21].

The number of randomly positioned available samples for the reconstruction is  $N_A \ll N$ . For a given *n* the available signal samples are at the positions

$$n+m \in \{n+m_1, n+m_2, \ldots, n+m_{N_A}\}.$$

The number of unavailable/missing samples is  $N_M = N - N_A$ . The available samples (measurements) of the windowed signal are then defined as

$$\mathbf{y}_{n} = [x(n+m_{1})w(m_{1}), \dots, x(n+m_{N_{A}})w(m_{N_{A}})]^{T}.$$
(6)

Note that

$$\mathbf{y}_n = \mathbf{AS}_N(n),$$

where **A** is the measurement matrix. The matrix **A** is obtained by keeping the rows of the inverse DFT matrix corresponding to the available samples

$$\mathbf{A} = \begin{bmatrix} \psi_0(m_1) & \psi_1(m_1) & \cdots & \psi_{N-1}(m_1) \\ \psi_0(m_2) & \psi_1(m_2) & \cdots & \psi_{N-1}(m_2) \\ \vdots & \vdots & \ddots & \vdots \\ \psi_0(m_{N_A}) & \psi_1(m_{N_A}) & \cdots & \psi_{N-1}(m_{N_A}) \end{bmatrix}$$
(7)

where  $\psi_k(m)$  are the inverse DFT matrix coefficients  $\psi_k(m) = \frac{1}{N} \exp(j2\pi mk/N)$ .

The goal of compressive sensing is to reconstruct the original sparse signal (using its windowed overlapped versions) from the available samples. A general compressive sensing formulation is

$$\min \|\mathbf{S}_N(n)\|_0$$
 subject to  $\mathbf{y}_n = \mathbf{A}\mathbf{S}_N(n)$ .

Here we will assume that the initial STFT is calculated using the available samples only

$$S_{N0}(n,k) = \sum_{i=1}^{N_A} x(n+m_i) w(m_i) e^{-j\frac{2\pi}{N}m_ik}$$
(8)

 $\mathbf{S}_{N0}(n) = N\mathbf{A}^{H}\mathbf{y}_{n},\tag{9}$ 

where superscript *H* denotes the Hermitian transpose.

The mean and the variance of this STFT, at a given instant n, calculated using the available signal samples only, are [15]

$$E\{S_{N0}(n,k)\} = \sum_{i=1}^{K} N_A A_i(n) \delta(k-k_i)$$
(10)

$$\operatorname{var}\{S_{N0}(n,k)\} = N_A \frac{N_M}{N-1} \sum_{i=1}^{K} |A_i(n)|^2 (1 - \delta(k - k_i)), \tag{11}$$

where  $\delta(k) = 1$  only for k = 0 and  $\delta(k) = 0$ , elsewhere.

In general, time-varying signals are not strictly sparse in the STFT domain. Because of their nature, most of these signals are either approximately sparse or nonsparse. A signal is *K*-sparse in a transformation domain (in our case, in the STFT domain) if it has only K ( $K \ll N$ ) nonzero coefficients in this domain at positions  $k \in \mathbb{K} = \{k_1, k_2, \ldots, k_K\}$ . Other coefficients, for  $k \notin \mathbb{K}$ , are zero-valued. A signal is approximately sparse if the coefficients for  $k \in \mathbb{K}$  are significantly larger than the coefficients at  $k \notin \mathbb{K}$ . A signal is not *K*-sparse if the coefficients for  $k \notin \mathbb{K}$  are order as the coefficients at the positions  $k \in \mathbb{K}$ . If we want to use the compressive sensing based theory for any of these signals the sparsity assumption has to be made. In this paper, we will analyze the error in these signals reconstructed under the *K*-sparsity assumption in the STFT domain.

Signal reconstruction is done using estimation of the nonzero coefficient positions, based on (8) and calculating the unknown coefficients  $A_i(n)$  based on the known signal values  $x(n + m_i)$ . Various reconstruction algorithms can be used. For the numerical verification of the results we will use an iterative form of the OMP algorithm. The reconstruction algorithm used in this paper is an iterative form of the OMP algorithm, introduced in [19,20]. Since the introduction of compressive sensing, many reconstruction algorithms can be found in [21]. The main reason to use the presented algorithm is the fact that it uses the sparsity assumption in an explicit way (producing *K* nonzero coefficients in the reconstructed signal). Also, its computational complexity is low. Other algorithms that also exploit the sparsity assumption in an explicit way can be used as well.

In the first step, the position of the maximal STFT coefficient is found as

$$k_1 = \arg \max{\mathbf{S}_{N0}(n)}$$

Matrix  $A_1$  is formed from matrix A by omitting all columns except the column corresponding to  $k_1$ . The first STFT estimate is

$$\mathbf{S}_{R}(n) = (\mathbf{A}_{1}^{H}\mathbf{A}_{1})^{-1}\mathbf{A}_{1}^{H}\mathbf{y}_{n}.$$

The signal is reconstructed and subtracted from the original signal at the positions of available samples. The STFT estimate is calculated again with this new signal and its maximum position  $k_2$  is found. A new set  $\mathbb{K} = \{k_1, k_2\}$  is formed with corresponding matrix  $\mathbf{A}_2$ . The new estimate  $\mathbf{S}_R(n)$  is calculated and the signal is reconstructed. The procedure is repeated *K* (assumed sparsity) times, with the final reconstruction

$$\mathbf{S}_{R}(n) = (\mathbf{A}_{K}^{H}\mathbf{A}_{K})^{-1}\mathbf{A}_{K}^{H}\mathbf{y}_{n}.$$

Download English Version:

## https://daneshyari.com/en/article/4977406

Download Persian Version:

https://daneshyari.com/article/4977406

Daneshyari.com