

28th International Symposium on Superconductivity, ISS 2015, November 16-18, 2015, Tokyo, Japan

## Multi-channel data acquisition system for a 500 m DC HTS power cable in Ishikari

Yury V. Ivanov<sup>a,b,\*</sup>, Noriko Chikumoto<sup>a,b</sup>, Hirofumi Watanabe<sup>a,b</sup>, Hirohisa Takano<sup>a,b</sup>,  
Noriyuki Inoue<sup>a,b</sup>, Satarou Yamaguchi<sup>a,b</sup>

<sup>a</sup>Center of Applied Superconductivity & Sustainable Energy Research, Chubu University, Kasugai, Aichi 487-8501, Japan

<sup>b</sup>Ishikari Superconducting DC Power Transmission System Research Association, 3-13 Moriya-cho, Kanagawa-ku, Yokohama 221-0022, Japan

---

### Abstract

Reduction of heat penetrating into the cryogenic region is the important method of optimization of superconducting devices. In the cases of short-range power transmission lines and compact HTS devices like magnets, the heat leakage through current leads is relatively large. In order to decrease this contribution, current leads equipped with Peltier elements can be used. The mentioned technology is being actively developed in the Chubu University. Commercial samples of Peltier current leads are installed at the terminals of 500-meter DC HTS cable in Ishikari (Hokkaido). This cable is designed for 5 kA. The inner conducting layer consists of 37 DI-BSCCO HTS tapes from Sumitomo Electric Industries, Ltd. with a critical current of 180 A; and the outer one consists of 35 tapes of the same type. Each end of the cable's tape is connected to the individual Peltier current lead. Accordingly, each of the two terminals is equipped with 72 Peltier current leads, 144 pieces in total. In order to examine behavior of the current leads in detail, each piece is supplied with two thermocouples; there are also voltage taps on feedthrough and on HTS tape end. In addition, current through Peltier current lead can be measured by means of individual current transformer. The hardware part of the data acquisition system includes four Keithley 3706A multimeters equipped with 60-channel model 3724 FET multiplexer cards. Therefore, 144 data blocks are formed. Furthermore, there are 72 measurements of a voltage drop across HTS tape. Sampling period is set to be 3 s. The program part of the data acquisition system was written using LabVIEW software solution (National Instruments Corp.).

© 2016 The Authors. Published by Elsevier B.V. This is an open access article under the CC BY-NC-ND license (<http://creativecommons.org/licenses/by-nc-nd/4.0/>).

Peer-review under responsibility of the ISS 2015 Program Committee

**Keywords:** DC HTS power transmission; Peltier current lead; Current imbalance; Data acquisition system

---

\* Corresponding author. Tel.: +81-568-51-9286 ; fax: +81-568-51-9413 .

E-mail address: [ivanov@isc.chubu.ac.jp](mailto:ivanov@isc.chubu.ac.jp)

## 1. Introduction

Development of superconducting power transmission (PT) lines that promises great benefits, has a very long history and is associated with overcoming significant engineering problems. The discovery of HTS in 1986 made it possible to simplify the design and reduce the cost of such systems largely. Thereafter, dozens of experimental AC HTS PT lines were created in different countries. Several hundred-meter cable length was achieved. Because DC HTS cables have many advantages, an upsurge in interest in using superconductors for DC power transfer was clearly observed in recent years. However, the number of DC projects in progress is still small [1-5].

One of the important advantages of DC HTS cables is the absence of AC losses. This fact greatly reduces the heat load on the cryogenic system. Since the energy consumption for maintaining the low temperature of the superconductor appears as transmission losses, the refinement of the efficiency of thermal insulation is an obvious way to improve the economic performance of DC HTS PT lines. Short-distance PT lines (for example, intra-plant) are characterized by the significant relative heat leak through the current leads. In the case of the compact systems like magnets, this contribution may be essential. Improvement of the thermal performance of the current lead is mainly achieved by optimizing their geometry and the use of different cooling methods. An alternative way is the application of "active self-cooled" current lead equipped with Peltier element connected in series. In this case, the thermoelectric element operates as a heat pump working against the flow of heat from the outside. Theoretical and experimental researches in the Chubu University allowed us to create commercial samples of Peltier current leads (PCLs) [1, 5-7]. Fig. 1 displays the off-the-shelf PCL design. Current model has four small Peltier elements connected in parallel.

Japanese largest project in the field of DC HTS PT has started in the city of Ishikari in Hokkaido on March 31, 2013. This national project is scheduled for three years. Two cable lines were built by the end of 2015 in the framework of the Ishikari project. 500-meter Line No. 1 connects Sakura Internet Inc. data center to the solar electric plant. 1000-meter Line No. 2 will be used for field study. Lines were designed with the aim of developing new technologies to bring the power transmission distance up to several tens, even hundreds of kilometers. Technical parameters of the Lines are summarized in the Table 1.

Table 1. Specification of the DC HTS PT lines in Ishikari.

	Line No. 1	Line No. 2
Length, type	Underground 500 m cable	Overland 1000 m cable
Rated parameters	5 kA, 20 kV, 100 MW	2.5 kA, 20 kV, 50 MW
HTS tapes	BSCCO (Type HT-CA) from Sumitomo Electric Industries, Ltd.	
Cable outer diameter	42 mm	40 mm
Inner conductor	37 HTS tapes ( $I_c > 190$ A)	24 HTS tapes ( $I_c > 190$ A)
Outer conductor	35 HTS tapes ( $I_c > 190$ A)	15 HTS tapes ( $I_c > 220$ A)
Cable insulation	PPLP	PPLP
Cooling system	1 x Turbo-Brayton (2kW@77K),	2 x Turbo-Brayton (2kW@77K),
	2 x Stirling (1kW@77K), 2 x Cryopump (40 l/min)	2 x Stirling (1kW@77K), 3 x Cryopump (40 l/min)

Among the differences from the standard HTS PT lines, it should be noted first the use of smooth cryogenic pipes instead of conventional corrugated ones. This approach enables to drastically reduce the hydraulic resistance to flow of the liquid nitrogen and thus to reduce the required power of the cryogenic pumps. Delivery of HTS cable separately from the cryostat and field assembly allows us to increase the drum length up to 5 km, reducing the number of joints and, consequently, reducing the accident risk. Second, the large-diameter outer pipes are utilized in order to improve the air-exhaust condition. Third, preliminary helical layout of the cable core inside the cryogenic pipe was used to prevent undesirable effects related to the thermal contraction. As far as cable is helically coiled along the walls of the inner pipe at the room temperature, and straight at the liquid nitrogen temperature, temperature change does not induce considerable longitudinal displacement. Residual cable strain can be compensated by the

Download English Version:

<https://daneshyari.com/en/article/1873189>

Download Persian Version:

<https://daneshyari.com/article/1873189>

[Daneshyari.com](https://daneshyari.com)