

4th International Conference on Process Engineering and Advanced Materials

Reactant Control System for Proton Exchange Membrane Fuel Cell

R.E. Rosli^a, A.B. Sulong^{a,b,*}, W.R.W. Daud^{a,c}, M.A. Zulkifley^d, M.I. Rosli^{a,c}, E.H. Majlan^a, M.A. Haque^a^aFuel Cell Institute, Universiti Kebangsaan Malaysia, 43600 UKM Bangi, Selangor, Malaysia^bDepartment of Mechanical & Material Engineering, Universiti Kebangsaan Malaysia, 43600 UKM Bangi, Selangor, Malaysia^cDepartment of Chemical Engineering, Universiti Kebangsaan Malaysia, 43600 UKM Bangi, Selangor, Malaysia^dDepartment of Electrical, Electronic and Systems Engineering, Universiti Kebangsaan Malaysia, 43600 UKM Bangi, Selangor, Malaysia

Abstract

The Proton Exchange Membrane Fuel Cell (PEMFC) has been a focus in many fuel cell studies for tremendous commercialization. It generates an efficient and reliable power with a suitable system to ensure its electrochemical reaction operates well. In this paper, a reactant system is being discussed. Significant parameters such as reactant pressure, flow rate and stoichiometric ratio are the major factors for a reliable performance. A fuel cell owning a complex structure with traditional reactant requirement generally gives an unsatisfactory performance when facing dynamic loading instances. Fuel starvation usually occurs especially during transients where the reactants consumed are higher than being supplied. This in turn causes a problem to the MEA components such as platinum particles agglomeration, carbon corrosion and even cell reversal problem that lead to degeneration of fuel cell. Hence, excess stoichiometric ratio need to be supplied to prevent this issue and ensure a dynamic operation at the same time avoid the wastage issues. A development of a system identification and control strategy for reactant system is significant to ensure a reliable performance of power production and longer life span of the fuel cell. Hydrogen was controlled according to the load variation and the reactant control system compensates the loading transient variation that meets the design requirements and produces a reliable performance. The Mass Flow Controller (MFC) meter used with the current input range between 0.004 to 0.020 A and was changed for the suitable supply of fuel flow accordingly. A Ziegler-Nicholes method used to tune the PID controller using a parameter of $K_c = 23,385$, $T_i = 0.011$ and $T_d = 0.002$. An optimum consumption of hydrogen observed with an average error from the overall reaction is 0.000423 A. From the result shown, the reactant control system build is competence to fulfill the loading demand.

© 2016 Published by Elsevier Ltd. This is an open access article under the CC BY-NC-ND license (<http://creativecommons.org/licenses/by-nc-nd/4.0/>).

Peer-review under responsibility of the organizing committee of ICPEAM 2016

Keywords: PEM fuel cell; on-line; non-linear dynamics; self tuning control; flow rate control; PID Controller

* Corresponding author. Tel.: +60389216678; fax: +60389259659.
E-mail address: sulongabubakar@gmail.com

1. Introduction

Fuel cell converts energy from chemical and produces electrical energy efficiently as a result from the electrochemical reaction between fuel (hydrogen) and oxidant (oxygen or air) as the reactant. They require a minimum maintenance due to their less moving parts [1]. There are various types of fuel cell being studied today and the most reliable fuel cell for stationary, portable electronics and vehicle applications is proton exchange membrane fuel cell (PEMFC). This is due to its low operational temperature, low noise, light weight, low corrosion, small volume and fast start-up capability which results in high energy density and quick start.

The amount of pressure and flow rate to be applied in the system is very complicated. Wherein an increase in flow rate will boost the kinetics of electrochemical reaction that result in higher power density and stack efficiency, but in the contrary this will also reduce the net available power from the fuel cell system. Usually, fuel is supplied in fixed amount but problem will arise during load variation where the fuel cell output power and current will increase [2, 3]. This problem needs a serious attention especially in vehicle or load variation applications as less hydrogen supply will cause power transient issue that leads to performance degradation, and subsequently poor response at higher load demand and also damaging MEA [4]. An excess hydrogen supply will issue the hydrogen wastage at lower current demand [5]. In order to overcome this problem, a controller needs to be implemented to control the flow rate of hydrogen being supplied to the fuel cell in the system.

In order to produce an efficient performance, the fuel cell needs a reactant management system where it functions to deliver the correct amount of supplies to generate power on demand [6]. There are many studies being done towards the control of fuel cell system, initiated by the complexity of the fuel cell. Reactant controls reported by many other researchers resulting in better performance where they presented an application of online self-tuning PID controller to prevent momentary drop during transient response caused by load variation [7]. This paper is focusing on the implementation of a reactant controller which is a design of feedback control system manipulating the flow rate of reactants being supplied into the fuel cell in order to improve the system response during load change. This will contribute to an increase of the fuel cell durability, capability and prevent the reactant waste.

2. Experimental Procedure

The single cell PEMFC used consists of a 25cm² of active area, graphite plate, silicone gasket, o-ring, MEA, current collector, and an aluminium end plate. The single cell was fueled by high purity hydrogen (99.99%) that being stored in a compressed gas cylinder which is reduced to 0.5 bar using a pressure regulator. The oxidant from purified air was also compressed in a gas cylinder reduced to 0.5 bar. The mass flow controller (MFC) used in this experiment was controlled by a PID type controller for an effective fuel supply at loading variation conditions. LabVIEW program with National Instrument (NI) devices was used to measure and record the values of the fuel cell performance on a real time basis. A programmable electronic load was used to generate a pulse current load profile. There are four flows of control algorithm, starting from fuel cell system, DAQ hardware tools (read), LabVIEW programme and DAQ hardware tools (write). These sequences keep running and analyzing as the system is powered. DAQ hardware tools were used to acquire data so that the signal can be sent out (control) and coming in (feedback). The setup of fuel cell testing was shown in Fig. 1.

3. Result & Discussion

Reactant pressure value is very much related to the flow rate [8]. When pressure was applied at constant value, the flow rate of gas proceeds into the graphite channel at fixed values, unless there is another controller that determines the value that flows through it. A controller is frequently used to ensure proper usage of the reactants and the power generated, in the sense that there is sufficient reactant flow rate during operating to improve the system efficiency. Fig. 2 shows the performance of the PEMFC with two levels of hydrogen flow rate at the pressure of 0.5 bar. Both conditions were tested with an increase of current periodically using DC electronic load. The polarization curves demonstrate that the load requirement can only be fulfilled if the fuel cell was supplied with a sufficient

Download English Version:

<https://daneshyari.com/en/article/853336>

Download Persian Version:

<https://daneshyari.com/article/853336>

[Daneshyari.com](https://daneshyari.com)